

8174/104-2403-11 Art. No. 139616



- Power supply in Ex d enclosures
- One to 72 cores are combined in one conductor bushing
- Versions: Screwable, pluggable
- For voltages up to max. 1000 V
- For conductor cross-sections up to 70 mm<sup>2</sup>

MY R. STAHL 8174A



The conductor bushings are used to connect the conductors between enclosures with the "flame-proof" and "increased safety" types of protection.

The cores are moulded with high-quality, leakage-current-resistant PU resin, meaning that they are insulated from the enclosure wall.

### Technical Data

#### Explosion Protection

Application range (zones)	1, 2
IECEX gas certificate	IECEX PTB 06.0081U
IECEX gas explosion protection	Ex db IIC Gb
IECEX firedamp certificate	IECEX PTB 06.0081U
IECEX firedamp protection	Ex db I Mb
ATEX gas certificate	PTB 01 ATEX 1065 U
ATEX gas explosion protection	Ex II 2 G Ex db IIC Gb
ATEX firedamp certificate	PTB 01 ATEX 1065 U
ATEX firedamp protection	Ex I M2 Ex db I Mb
Certificates	ATEX (PTB), China (CQST), IECEX (PTB)

#### Electrical Data

Rated operational voltage AC	750 V
Rated operational current	15 A

#### Ambient Conditions


Ambient temperature	-40 °C ... +110 °C
---------------------	--------------------

#### Mechanical Data


Ex d conductor length	1000 mm
Ex e conductor length	1000 mm
Min. conductor cross section	2.5 mm <sup>2</sup>
Number of core ends	24
Thread size	M42
Thread pitch	1,5
Cable colour	Black
Weight	1.7 kg
Weight	3.74 lb

8174/104-2403-11    Art. No. 139616

Technical Drawings – Subject to Alterations



Accessories

Jam nut		Art. No.
	M42 x 1.5	108378

We reserve the right to make alterations to the technical data, dimensions, weights, designs and products available without notice. The illustrations cannot be considered binding.