Installation equipment and accessories

Conductor bushing



8174/104-2101-66 Art. No. 139576



- Power supply in Ex d enclosures
- · One to 72 cores are combined in one conductor bushing
- Versions: Screwable, pluggable
- For voltages up to max. 1000 V
- · For conductor cross-sections up to 70 mm²

MY R. STAHL 8174A



The conductor bushings are used to connect the conductors between enclosures with the "flame-proof" and "increased safety" types of protection.

The cores are moulded with high-quality, leakage-current-resistant PU resin, meaning that they are insulated from the enclosure wall.


Technical Data

Explosion Protection		
Application range (zones)	1, 2	
IECEX gas certificate	IECEx PTB 06.0081U	
IECEx gas explosion protection	Ex db IIC Gb	
IECEX firedamp certificate	IECEx PTB 06.0081U	
IECEx firedamp protection	Ex db I Mb	
ATEX gas certificate	PTB 01 ATEX 1065 U	
ATEX gas explosion protection	ll 2 G Ex db IIC Gb	
ATEX firedamp certificate	PTB 01 ATEX 1065 U	
ATEX firedamp protection	l M2 Ex db l Mb	
Certificates	ATEX (PTB), China (CQST), IECEx (PTB)	
Electrical Data		
Rated operational voltage AC	750 V	
Ambient Conditions		
Ambient temperature	-40 °C +110 °C	
Mechanical Data		
Ex d conductor length	600 mm	
Ex e conductor length	600 mm	
Min. conductor cross section	0.75 mm ²	
Number of core ends	21	
Thread size	M42	
Thread pitch	1,5	
Cable colour	Black	
Weight	100 g	
Weight	0.22 lb	



8174/104-2101-66 Art. No. 139576

Technical Drawings – Subject to Alterations



Accessories

.

Jam nut		Art. No.
	M42 x 1.5	108378

We reserve the right to make alterations to the technical data, dimensions, weights, designs and products available without notice. The illustrations cannot be considered binding.