## Installation equipment and accessories

## Conductor bushing



### 8174/203-0304-33 Art. No. 139677



- · Power supply in Ex d enclosures
- · One to 72 cores are combined in one conductor bushing
- · Versions: Screwable, pluggable
- For voltages up to max. 1000 V
- For conductor cross-sections up to 70 mm<sup>2</sup>

## MY R. STAHL 8174A



The conductor bushings are used to connect the conductors between enclosures with the "flame-proof" and "increased safety" types of protection.

The cores are moulded with high-quality, leakage-current-resistant PU resin, meaning that they are insulated from the enclosure wall.

#### **Technical Data**

Explosion Protection	
Application range (zones)	1, 2
IECEX gas certificate	IECEx PTB 06.0081U
IECEx gas explosion protection	Ex db IIC Gb
IECEX firedamp certificate	IECEx PTB 06.0081U
IECEx firedamp protection	Ex db I Mb
ATEX gas certificate	PTB 01 ATEX 1065 U
ATEX gas explosion protection	
ATEX firedamp certificate	PTB 01 ATEX 1065 U
ATEX firedamp protection	
Certificates	ATEX (PTB), China (CQST), IECEx (PTB)
Electrical Data	
Rated operational voltage AC	750 V
Rated operational current	25 A
Ambient Conditions	
Ambient temperature	-40 °C +110 °C
Mechanical Data	
Socket diameter	ø 34
Ex d conductor length	1300 mm
Ex e conductor length	1300 mm
Min. conductor cross section	4 mm <sup>2</sup>
Number of core ends	3
Thread size	M42
Thread pitch	1,5
Cable colour	Black
Weight	468 g
Weight	1.03 lb


# Installation equipment and accessories

## Conductor bushing



## 8174/203-0304-33 Art. No. 139677

### **Technical Drawings – Subject to Alterations**



### **Accessories**

109806
Art. No
252066
Art. No
139720
Art. No
140032

We reserve the right to make alterations to the technical data, dimensions, weights, designs and products available without notice. The illustrations cannot be considered binding.